

XBA mini-USD6

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT104U/ICT104V)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

XBA mini dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject USD 1	ON											
★	Accept USD 1	OFF											
★	Reject USD 5		ON										
★	Accept USD 5		OFF										
★	Reject USD 10			ON									
★	Accept USD 10			OFF									
★	Reject USD 20				ON								
★	Accept USD 20				OFF								
★	Reject USD 50 & 100					ON							
★	Accept USD 50 & 100					OFF							
★	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★	Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★	Colorful light							OFF	OFF				
★	The green light flashes							OFF	ON				
★	Reserved							ON	OFF				
★	No light							ON	ON				
★	Inhibit Active High									ON			
★	Inhibit Active Low									OFF			
★	Reserved										ON		
★	Reserved										OFF		
★	Interface Timing Conversion	5ms LO / 5ms HI									OFF	OFF	
		5ms LO / 10ms HI									ON	OFF	
		10ms LO / 10ms HI									OFF	ON	
		20ms LO / 20ms HI									ON	ON	

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Calibration card is needed.

XBA mini-USD6(Pulse/MDB/JPSTD/ICT104U/ICT104V)

Interface Settings: 2(Pulse)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / USD 1			OFF	OFF
	2 pulses / USD 1			OFF	ON
	4 pulses / USD 1			ON	OFF
	20 pulses / USD 1			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104U)

	INTERFACE	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
★	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

	INTERFACE	SW1	SW2	SW3	SW4
★	Connect with coin changer	ON			
	Connect with ICT JPSTD Converter board	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
★	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	MDB Mode			OFF	OFF
	JPSTD Mode			OFF	ON
★	ICT104U Mode			ON	OFF
	ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	JPSTD	Pulse	MDB
BV1	1	1	1	1	1
BV2	5	5		5	
BV3	10	10		10	5
BV4	20	20		20	10
BV5	50	50		50	20
BV6	100	100		100	50
BV7					100